



## DIM 700 DC/NR - 28W 500/700mA

Australian approved dimmable constant current LED driver with selectable Power and CCT

### Application

The perfect choice for constant current electronic lighting circuits

### Design Specifications

- Compact design, SELV, electrical class II, EMC compliant
- Safe no load, overload, short circuit protection
- Onboard selectable output current (500/700mA)
- Integral selectable CCT with approved SAL products
- Dimmable with a trailing edge dimmer, delivering flickerCONTROLLED driver performance
- Recommended SAL trailing edge dimmers SDD350UM, SDD400U, SDD300BTAM, SDA450U/LED, Electrical class II, Do Not Cover



### Performance

- Dimmable - **YES**
- Dimmer Type - **TRAILING EDGE**



### Technical Specification

Product	Model No.	Input Voltage (V/AC)	Frequency (Hz)	Output Current (mA)	Power (W)	Power Factor
	DIM700/28DC/NR	240	50	700	28	0.9

Dimmable	Dim (mm)
YES	179(L) x 45(W) x 30(H)

Due to continued product and technology enhancements, data sourced from sal.net.au shall not form part of any contract and or technical performance guarantee unless expressly confirmed in writing by SAL at the time of order. Products are sold in accordance with SAL Terms and Conditions of sale and all images shown are for illustration purposes only and may vary from the actual colour or finish. Unless specifically stated, all IP ratings nominated for Interior products are from "below the ceiling".



## Dimensions

### Wiring Diagram

